INVERTER TECHNOLOGY POWERS SENSITIVE ELECTRONIC & ELECTRICAL EQUIPMENT!



2000W



PT2200i

DIGITAL INVERTER GENERATOR

2000W PEAK POWER, 1800W RATED POWER

IDEAL FOR CAMPING AND HOME USE APPLICATIONS.

1 x 15A 230V AC OUTLET - ideal for operating lighting, small fridge/freezers, fans and much more.

TWIN USB OUTLETS - ideal for charging small sensitive electronics.

LARGE CAPACITY MUFFLER FOR QUIET OPERATION - minimizes engine noise, ideal for use anywhere a quiet source of electrical power is required.

5 LITRE FUEL TANK - for up to 6 hours continuous operation.

SIMPLE AND RELIABLE ELECTRONIC IGNITION SYSTEM -

makes starting easier every time.

HIGH PERFORMANCE AIR CLEANER SYSTEM - greatly reduces engine wear and improves performance.

THERMAL OVERLOAD CIRCUIT BREAKERS cut the power in the event of an electrical overload offering greater safety.

perfect power Guaranteed Pure Sine Wave



Optional Parallel Connection



Synchronise two units for increased power demands up to 3400W

SKU 354829





POWER OUTLET



TWIN USB OUTLETS



PURE SINE WAVE

OUTPUT (Max)	AMPS (Max)	OUTPUT (Rated)	ENGINE Type	STARTING System	FUEL TANK Capacity	RUN Time	POWER OUTLETS	LxWxH	WEIGHT
2000W	7.8A	1800W	4 Stroke	Recoil	5L	6 hrs	1	498 x 298 x 459mm	22kg